

NADITBNC-F

Female XLR chassis connector 110 Ω input - female BNC 75 Ω output. Interface balanced and coaxial lines.

Features & Benefits

- Allow long cable runs for digital audio signals via low attenuation coax lines
- Match balanced to coaxial lines
- Match impedances 110 Ω to 75 Ω
- Simple to use, passive units



Technical Information [hide](#)

Product

Title	NADITBNC-F
-------	------------

Connection Type	Adapter
-----------------	---------

Gender	female
--------	--------

Electrical

Frequencyrange	0.1 - 6 MHz
----------------	-------------

Rated voltage	≤ 5 V p-p
---------------	----------------

VSWR	< 1.1
------	-------

Return loss	> 26.4 dB
-------------	-----------

Insertion Loss	< 0.3 dB @ 0.1 MHz to 10 MHz
----------------	------------------------------